

Tehnički list za artikl: LID16998--

# DALI & PUSH TO DIMM 40W DRIVER CONSTANT CURRENT 230V

DIP switch prekidač



## Tehnički podaci

|                         |                                                                                                  |
|-------------------------|--------------------------------------------------------------------------------------------------|
| Dimabilno               | DALI<br>Da<br>Push DIM                                                                           |
| IP stupanj zaštite      | IP20                                                                                             |
| Faktor snage            | 0,95                                                                                             |
| Snaga (W)               | 2,4-40                                                                                           |
| Ulazni napon AC (V)     | 220-240                                                                                          |
| Pogonska struja mA (mA) | 400mA, 450mA, 500mA, 550mA, 600mA, 650mA, 700mA, 750mA, 800mA, 850mA, 900mA, 950mA, 1000mA, 1050 |
| Izlazna struja (A)      | 0,4-1,05                                                                                         |
| Materijal               | Plastika                                                                                         |
| Duljina (mm)            | 285                                                                                              |
| Širina (mm)             | 30                                                                                               |
| Visina (mm)             | 21                                                                                               |
| (DxŠxV) mm              | 285x30x21                                                                                        |

**Mjerne skice: DALI & PUSH TO DIMM 40W DRIVER CONSTANT CURRENT 230V**

| OPIS                                                                        | KAT. BROJ |
|-----------------------------------------------------------------------------|-----------|
| DALI & PUSH TO DIMM 40W DRIVER CONSTANT CURRENT 230V<br>DIP switch prekidač | LID16998  |